


DIMENSION SHEET

Ref : 00065
Date : 19/09/03
Issue : A
Page : 1 of 1

Input/Output Reactors suitable for SJ300 Inverters

Case Dimensions (mm)

Hitachi Inverter	Suitable Choke	A	B	C	D	E	Weight in Kg
SJ300 007 HFE	RL00202	112	104	71	50	37	1.8
SJ300 015 HFE	RL00403	112	104	86	60	37	2.3
SJ300 022 HFE	RL00803	152	122	86	67	51	5.0
SJ300 040 HFE	RL00802	152	122	76	53	51	3.6
SJ300 055 HFE	RL01202	152	127	84	53	51	8.2
SJ300 075 HFE	RL01802	152	135	89	63	51	5.5
SJ300 110 HFE	RL02502	183	147	89	60	76	6.4
SJ300 150 HFE	RL03502	183	147	102	70	76	7.3
SJ300 185 HFE	RL04502	229	188	119	80	76	13.0
SJ300 220 HFE	RL04502	229	188	119	80	76	13.0
SJ300 300 HFE	RL05502	229	178	135	80	76	12.0
SJ300 370 HFE	RL08002	274	216	165	88	92	23.0
SJ300 450 HFE	RL08002	274	216	165	88	92	23.0
SJ300 550 HFE	RL10002	279	216	170	93	92	23.0
SJ300 750 HFE	RL13002	274	216	172	93	92	28.0
SJ300 900 HFE	RL20003	274	216	254	150	92	46.0
SJ300 1100 HFE	RL20003	274	216	254	150	92	46.0
SJ300 1320 HFE	RL25002	381	290	286	148	117	65.0



HID LTD

Vantage House, Harfreys Road, Great Yarmouth, Norfolk, NR31 0LS
Tel: 01493 442525 Fax: 01493 442323 Email: sales@hid.co.uk Website: www.hid.co.uk